Application No.: 09/885,937                    Attorney Docket No. 0465-0840P
Art Unit 2637                                 Amendment filed December 13, 2004
                                                                     Page 5

## Amendments to the Claims

What is claimed is:

1.     (currently amended) An apparatus for generating finite impulse response (FIR)
filter coefficients comprising:

(a) an address generator that multiplies a desired cutoff frequency $f_i$ by an integer $n$ ~~based on an outside control signal~~ to generate an address;

(b) a first look-up table that generates a sine function value of said address;

(c) a divider that divides said sine function value by $n\pi$;

(d) a multiplexer that generates an impulse response function value by selecting one of a first value provided by said divider and $2f_i$ based on ~~an~~ said outside control signal; and

(e) a multiplier that multiplies said impulse response function value by a corresponding window function value to generate an $n$th filter coefficient value.

2.     (currently amended)   The apparatus of claim 1, wherein said multiplexer generates said impulse response function value by selecting said first

value if $n$ is equal to [[0]] zero or by selecting $2f_i$ if $n$ is not equal to [[0]] zero.

3.    (currently amended)  The apparatus of claim 1, wherein n=0, 1, 2,...,N-1 where $N$ represent a number of said ~~FIR filter taps~~ coefficients.

4.    (currently amended)  The apparatus of claim 1, wherein said $n$th filter coefficient value can be non-zero only when $-\dfrac{N-1}{2} \leq n \leq \dfrac{N-1}{2}$, where $N$ represents a number of said ~~FIR~~ filter ~~taps~~ coefficients.

5.    (currently amended)  The apparatus of claim 1, wherein said ~~corresponding~~ window function value is obtained by using any one of Rectangular, Bartlett, Hanning, Hamming, and Blackman window functions.

6.    (original)  The apparatus of claim 1, further comprising a second look-up table that receives ∧the integer n and generates said corresponding window function value.

7.   (currently amended)  An apparatus for generating low-pass or, high pass or band-pass FIR filter coefficients using more than one low-pass filter coefficient generating devices having different desired cutoff frequencies, the

Application No.: 09/885,937          Attorney Docket No. 0465-0840P
Art Unit 2637               Amendment filed December 13, 2004
                                     Page 7

apparatus comprising:

(a) at least two low-pass filter coefficient generating devices, each of said devices comprises

(a1) an address generator that multiplies a desired cutoff frequency $f_i$ by an integer $n$ ~~based on an outside control signal~~ to generate an address,

(a2) a first look-up table that generates a sine function value of said address,

(a3) a divider that divides said sine function value by $n\pi$,

(a4) a multiplexer ~~multiplexter~~ that generates an impulse response function value by selecting one of a first value produced by said divider and $2f_i$ based on ~~an~~ said outside control signal, and

(a5) a multiplier that multiples said impulse response function value by a corresponding window function value to generate an $n$th low-pass filter coefficient value; and

(b) an adder coupled to said devices for generating an $n$th low pass, or high-pass or band pass filter coefficient value by adding ~~or subtracting~~ each of said ~~$N$th~~ $n$th low-pass~~, high-pass or band-pass~~ filter ~~coefficients~~ coefficient values generated by said devices in the step (a5).

8. (currently amended) The apparatus of claim 7, wherein said multiplexer generates said impulse response function value by selecting said first

Application No.: 09/885,937                    Attorney Docket No. 0465-0840P
Art Unit 2637                                  Amendment filed December 13, 2004
                                                                        Page 8

value if n is equal to [[0]] zero or by selecting $2 f_i$ if n is not equal to [[0]] zero.

9.     (currently amended)    The apparatus of claim 7, wherein

n=0,1,2,...,N-1, where N represents a number of said FIR filter taps coefficients.

10.    (currently amended)    The apparatus of claim 7, wherein wherein

said $n$th filter coefficient value generated in the step (b) can be nonzero only

when $-\frac{N-1}{2} \leq n \leq \frac{N-1}{2}$, where N represents a number of said FIR filter taps

coefficients.

11.    (currently amended)    The apparatus of claim 7, wherein said

corresponding window function value is obtained by using any one of

Rectangular, Bartlett, Hanning, Hamming and Blackman window functions.

12.    (original)    The apparatus of claim 7, wherein each of said devices

further comprises a second look-up table that receives the integer $n$ and generates said

corresponding window function value.

13.    (currently amended)    A method for generating finite impulse

response (FIR) filter coefficients, the method comprising,

Application No.: 09/885,937          Attorney Docket No. 0465-0840P
Art Unit 2637                Amendment filed December 13, 2004
                                         Page 9

      (a)      generating an address by multiplying a desired cutoff frequency $f_i$ by an integer $n$ ~~based on an outside control signal~~;

      (b)      generating a sine function value of said address;

      (c)      dividing said sine function value by $n\pi$;

      (d)      generating an impulse response function value by selecting one of a first value produced from said division in the step (c) and $2f_i$ based on ~~an~~ said outside control signal; and

      (e)      generating an nth filter coefficient value by multiplying said impulse response function value by a corresponding window function value.

      14.    (original)   The method of claim 13, wherein said impule response function value is generated by selecting said first value if $n$ is equal to zero or by selecting $2 f_i$ if $n$ is not equal to zero.

      15.    (currently amended)   The method of claim 13, wherein n=0,1,2,..., N-1, where N represents a number of ~~said FIR~~ filter ~~taps~~ coefficients.

      17 ~~16.~~    (currently amended)   The method of claim 13, wherein said nth filter coefficient value can be non-zero only when $-\frac{N-1}{2} \le n \le \frac{N-1}{2}$, where N represent a number of ~~said FIR~~ filter ~~taps~~ coefficients.

Application No.: 09/885,937
Art Unit 2637

Attorney Docket No. 0465-0840P
Amendment filed December 13, 2004
Page 10

19 17. (currently amended) The method of claim 13, wherein said corresponding window function value is obtained by using any one of Rectangular, Bartlett, Hanning, Hamming, and Blackman window functions.

20 18. (original) The method of claim 13, wherein said corresponding window function value is a $(n+(N-1)/2)$th window function value, wherein N represents the number of filter coefficients.

16 19. (new) The method of claim 15, wherein the number of said FIR filter coefficients is determined by a number of taps.

18 20. (new) The method of claim 16, wherein the number of said FIR filter coefficients is determined by a number of taps.